# DH-DVR0404ME-U/ME-H

### 4 Channel Mobile Standalone DVR





**DH-DVR0404ME-U:** 4 channel video inputs and 4 channel audio inputs. The 1st channel support 25/30fps at D1 and others channel support 25/30fps at CIF recording. It can support TV, VGA and USB2.0. GPS, Wi-Fi, 3G and SD card are optional.

**DH-DVR0404ME-H:** 4 channel video inputs and 4 channel audio inputs. It can support 100/120fps at D1 resolution recording. It can support TV, VGA and USB2.0. GPS, Wi-Fi, 3G and SD card are optional.

#### **Features**


- 4 channel mobile standalone DVR
- H.264 video compression algorithm ideal
- 1DIN compact size(the car CD machine standard size) and standard car electronic interface, easy for embedded installation
- Multi-information display and recording: Car Number, Time, Channel, GPS, Speed, support freely setting of overlay and recording
- Watermark technology prevent video data tampering, to ensure the authenticity of the record

- Support wide voltage car power supply input(8~60V), protection of overvoltage, under-voltage, short circuit and over-current
- Air connector interface used, provide excellent waterproof, shockproof performance
- Pluggable HDD-case used, provide powerful vibration-proof capability
- Multi-Interface such as USB 2.0, Ethernet port, RS232,RS485 port, VGA, Alarm in/out etc
- $\bullet$  Built-in web server, multi-DVR client, DMSS & CMS

#### **Rear Panel**



## Dimension(mm)







# **Specifications**

Main Processor	High performance embedded microprocessor	
	riigii periornance embedded microprocessor	
Operating System	Embedded LINUX	
System Resources	Pentaplex function: live, recording, playback, backup & remote access	
Control Mode	USB mouse, IR remote control, Keyboard, Network	
Input	4 channel, Air connector to BNC(1.0Vp-p, 75Ω)	
Standard	NTSC(525Line, 60f/s), PAL(625Line, 50f/s)	
Output	2 TV(1 Air connector to BNC, 1port extension), 1 VGA(RJ45 port extension)	
Input	4 channel, Air connector to BNC(200-2800mV, 30KΩ)	
Output		
Bidirectional Talk	1 channel Input, (200-2800mV, 30KΩ), 1 channel Output, (200-3000mV, 5KΩ), 4-pin port extension	
Display Split	1/4 1280×1024, 1280×720, 1024×768, 800×600	
Resolution		
Tour Display	Support	
Privacy Masking	4 self-defined four-sided zones for privacy masking for each camera	
OSD	GPS information, Camera name, time, video loss, camera lock, motion detection, recording	
Video/Audio Compression	H.264 / PCM	
Image Resolution	D1/4CIF(704×576/704×480) / HD1(352×576/352×480) / 2CIF(704×288/704×240) / CIF(352×288/352×240) / QCIF(176×144/176×120)	
Encoding Speed	Main Stream:	Main Stream:
	Channel 1: D1/CIF/QCIF (1~25/30fps);	D1/HD1/2CIF/CIF(1~25/30fps),
	Channel 2~4: CIF/QCIF (1~25/30fps), D1 (1~6/7fps)	
	Extra Stream: QCIF(1~25/30fps), CIF(1-6/7fps)	Extra Stream: CIF/QCIF(1~25/30fps)
Bit Rate	32~2048Kb/s	
Image Quality	y 1~6 level (level 6 is the best, VBR effectively)	
Recording Mode Manual, Schedule(Regular(Continuous), MD(Video detection: Motion detection, Camera blar		on: Motion detection, Camera blank, Video loss), Alarm), Stop
Recording Priority	Manual > Alarm > MD > Regular	
Recording Interval	1~120 min. (default: 60 min.), Pre-record: 1~30 sec., Post	-record: 10~300 sec.
Trigger Events	Recording, PTZ movement, Tour, Alarm, Email, Snapshot	
Motion Detection	Zones: 396(22×18), Sensitivity: 1~6 (level 6 is highest)	
Video Loss & Camera Blank	Support	
Alarm Input	7 channel	
Relay Output	2 channel	
Playback Channel	1/2/4	
Search Mode	Time/Date, Alarm, Motion Detection & Exact search (accurate to second)	
Playback Functions	Play, Pause, Stop, Rewind, Fast play, Slow play, Next file, Previous file, Next camera, Previous camera, Full screen, Repeat, Shuffle, Backup selection, Digital zoom(any size)	
Rackun Mode	Pluggable HDD-case / Flash drive / USB HDD / USB CD / [	DVD-RW / Network download
	RJ-45 port (10/100M)	
	TCP/IP, UDP, DHCP, DNS, IP Filter, PPPOE, DDNS, FTP, Email, Alarm Server	
	Monitor, PTZ control, Playback, System setting, File download, Log information	
·		
	. 55	
		aid(Redundancy)
-	3,. ,	na(neadinaticy)
	PTZ control	
	<u>'</u>	
Dimension		
	178mm×220mm×50mm(W×D×H)  2.1KG(with HDD)	
Weight		
Weight Vibration-proof		
Vibration-proof	5Hz~300Hz: X / Y / Z each direction 8 hours 5Hz~11Hz: Vibration amplitude 10mm	
	Control Mode Input Standard Output Input Output Bidirectional Talk Display Split Resolution Tour Display Privacy Masking OSD Video/Audio Compression Image Resolution Encoding Speed  Bit Rate Image Quality Recording Mode Recording Priority Recording Interval Trigger Events Motion Detection Video Loss & Camera Blank Alarm Input Relay Output Playback Channel Search Mode Playback Functions  Backup Mode Ethernet Wi-Fi 3G Network Functions Remote Operation Hard Disk SD Card Space Occupation HDD Management USB Interface RS232 RS485 GPS Power Supply Power Consumption Working Environment	Control Mode USB mouse, IR remote control, Keyboard, Network Input 4 channel, Air connector to BNC(1.0Vp-p, 75Q) Standard NTSC(525Line, 601/s), PAL(625Line, 501/s) Output 2 TV(1 Air connector to BNC, 1) port extension), 1 VGA(RJ4 Input 4 channel, Air connector to BNC(200-2800mV, 30KQ) Input 1 channel, Air connector to BNC(200-3800mV, 30KQ) Ustput 1 channel input, (200-2800mV, 30KQ), 1 channel Output, Display Split 1/4 Resolution 1 1280×1024, 1280×720, 1024×768, 800×600 Tour Display Support Privacy Masking 4 self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined four-sided zones for privacy masking for exit of the self-defined fo